



Increases the possibilities of the NYX Bulb and SolaBulb:


- Powers the bulb via integrated DC cable
- Acts as remote display to program the bulb
- Bulb can be attached to PowerStation via dummy lamp socket
- Helps to mount attached bulb via the integrated magnets or via mounting accessories which can be connected to the PowerStation's Airline Track at side or bottom

SPECIFICATIONS

Order Codes	FP5-PS
Battery Runtime	up to 20 hours
Battery Lifetime	70 % after 300 cycles
Charging Time (nominal)	5 hours
Battery Runtime (max. Brightness)	3 h 15 m
DC Input	24 VDC / 0.7 A - 48 VDC / 0.35 A
DC Connectors IN / OUT	5.5 mm / 2.1 mm (IN) 3.5 mm / 1.35 mm (OUT)
Battery	3 350 mAh / 10.8 V
Wired DMX	No
Wired DMX	0 - 40 °C / 32 - 104 °F
Weight	0.4 kg / 0.89 lbs
Dimensions (L x W x D)	96 mm x 80.8 mm x 42.4 mm / 3.8" x 3.2" x 1.7"
Mounting Options	3x Airline Tracks, Magnets

All specifications provided are typical values and maybe subject to change without prior notice.

DRAWINGS



ACCESSORIES

Lamp Socket
FP5-E27S



included with each
single NYX Bulb

TrackPin
AX-TP



**PowerStation
Hanger**
FP5-PSH



Power Supply Unit
AX1-CHR



PowerStation Charging Case
FP5-PS-CHRCSE



FUNCTIONS



Dummy Lamp socket for
mounting on PowerStation

Airline tracks for more
mounting options

4 Magnets for
easy mounting

Remote your NYX Bulb. Easy
access to DMX setup, colors
and hue, saturation, intensity
control



POWERSTATION SET

FP5-PS-SET



Charge PowerStations
directly in the case.

Order Code: FP5-PS-SET-EU - / US - / UK - / CH - / AU
Dimensions (L x W x D):
520 x 400 x 140 mm
20.5" x 15.7" x 5.5"
Weight (full): 13.4 kg / 29.54 lbs

Can hold

- 8x PowerStation**
(FP5-PS)
- 8x PowerStation Hanger**
(FP5-PSH)
- 8x Lamp Socket**
(FP5-E27S)
- 8x TrackPin**
(AX-TP)
- 8x BridgeCable**
(FP5-PS-BC)
- 1x PSU**
(AX1-CHR)
- 1x DC SplitCable**
(FP5-DTSC)

SETS - PROGRAMING



Program NYX Bulbs with the included PowerStation one by one.



Connect the 8 Powerstations with Bridge Cables to the 8 NYX Bulbs for setting them up all together.